

## SQ7+

### Overview



With a 48-input channel 96kHz XCVI core for ultra-low latency and phase coherent mixing, alongside incredible connectivity options - the SQ range continues to be class leading and the go-to solution for owner operators, mid-sized venues, small tours and anywhere audio quality and interoperability are vital.

The SQ7+ upgrades the SQ-7 with more processing power, a larger 9" touchscreen with reimagined GUI and a clean 'carbon-on-graphite' update to the surface artwork and controls.

All SQ+ models also include 4x RackUltra FX engines with dedicated send and return channels and the ability to run the latest DEEP channel processing.

- 96kHz XCVI Core
- 48x Input Processing Channels
- Stereo Main LR
- 12x Mono/Stereo, Group/Aux Mixes
- 4x FX Sends
- 4x RackUltra FX Sends
- 6x Mono/Linkable Matrix
- 32x XLR Mic/Line Input Sockets
- 3x Stereo Line Input Sockets (2x TRS, 1x 3.5mm Stereo Jack)
- 1x XLR Talkback Socket
- 16x XLR Output Sockets
- 2x TRS Output Sockets
- 1x AES3 Stereo Digital Output Socket
- 128x128 Intelligent SLink Port for Everything I/O expansion and system connections
- Stereo Headphone Output
- 8x FX Engines with dedicated Stereo Return Channels
- 4x RackUltra FX Engines with dedicated Stereo Return Channels
- 9" Capacitive Touchscreen
- 33x 100mm Motorised Faders
- 6x Customisable Channel Strip Layers
- 16x Soft Keys
- 8x Soft Rotaries
- USB-A stereo/multichannel audio record/playback and data transfer
- USB-B Audio interface for multichannel record/playback (32x32)
- Configurable dual Footswitch Connection
- Configurable Chromatic Channel Meter LED's
- IEC Mains Connection with Worldwide PSU
- RJ45 Network Socket
- Remote network control via free apps