

ATEM 1 M/E Advanced Panel 30



The ATEM 1 M/E Advanced Panel 30 features a single M/E row, 30 input button design that is ideal for switching big productions from desk surfaces that are not deep enough for a bigger panel. It has 3 independent system control LCDs plus it can control up to 4 M/Es in larger switchers. All input buttons include LCDs for custom labeling and it also includes an independent select bus! Dual power inputs provide redundancy and the built-in 4 port Ethernet switch means no additional network equipment is needed so it will fit even the most challenging live production spaces!

\$5,645


Connections

Ethernet

 $4 \times 10/100/1000$ BASE-T with loop output for additional control panels or computers.

Software Updates

1 x USB-C for firmware updates.



Product Specifics

Number of Mix Effects RowsPreview TransitionDedicated Macro Buttons11 x 30Direct Cross PointsTransition Rate DisplaysTransport Control Buttons30Via main menu8Shifted Cross PointsLCD Menu DisplaysDestination Bus6031

Crosspoint Button Type Tri-Color LED Menu Control 3 x 20 buttons

Silcioi

Source Select Bus

1

Fader Bar 3 Axis Joystick Numeric Keypad
1 1 1

Software

Software Applications

ATEM Software Control Panel.

Operating Systems



Mac 11.1 Big Sur, Mac 12.0 Monterey or later.



Windows 10 and 11.

Power Requirements

Input Voltage 2 x Internal 100 - 240V AC. **Redundant Power** Yes Power Usage 80W

Physical Specifications





Environmental Specifications

Operating Temperature 0° to 40° C (32° to 104° F)

Storage Temperature -20° to 60° C (-4° to 140° F) **Relative Humidity** 0% to 95% non-condensing

What's Included
ATEM 1 M/E Advanced Panel 30 Welcome wallet with QR code for software download
Warranty
12 Month Limited Manufacturer's Warranty.
All items on this website are copyright Blackmagic Design Pty. Ltd. 2023, all rights reserved. All trademarks are property of their respective owners. MSRP includes duties, but excludes sales tax and shipping costs. This website uses remarketing services to advertise on third party websites to previous visitors to our site. You can opt out at any time by changing cookie settings. Privacy Policy
Blackmagic Design Authorized Reseller